Digital Scale User Manual

Thank you for purchasing our pocket scale. We are confident that with normal use and proper treatment your scale will provide you with years of reliable service. Please read all the operation instructions carefully before you use your new scale.

Display Messages:

- **LO** – Low battery; please change the batteries in the scale.
- **OuEr**- The load cell of the scale is being overloaded. You need to remove the excessive weight from the scale immediately.
- **UnSt** – The scale is placed on an unstable surface, please move the scale to a more stable surface.
- **rCAL** – the scale can not return to zero, please recalibrate the scale.
- **CAL** – This is the prompt for beginning the calibration process of your scale. You will see this message when you press and hold the Cal button on

your scale. Once this message appears, you must release the button and follow the remaining steps for calibrating your scale.

- **PASS** – you have successfully calibrated your scale, you are now able to use the scale.
- **FAIL** – Calibration has failed, please make sure you have the scale on a stable surface and that you are using the correct weight to calibrate the scale. Try to calibrate the scale following the calibration instructions exactly.

Instructions:

ON/OFF FUNCTION
Place your scale on a flat and stable surface away from any electronic equipment that may interfere with the scale. Press and release the ON/OFF button, wait until the display shows "0.00" and the zero-stable sign "⏚", you may now place the object you want to weigh on the platform. The scale can be read when the lock sign "⏚" is shown in the display.

TARE FUNCTION.

Turn on the scale as described above, place the "tare item" on the platform, press the "ZERO" button to zero out the display, when "0.00" appears on the screen you may now place items on the scale to be weighed. Once you are finished weighing, remove all objects from the scale, press the "ZERO" again to cancel the TARE FUNCTION.

RETURN TO ZERO
After weighing an item, if the display does not read "0.00" press the ZERO button to return to "0.00" and you are ready to weigh again.

CHANGE WEIGHING MODES
Press the "MODE" button to change weighing modes on your scale. This scale has 4 weighing modes: g, oz, gn, ct

CALIBRATION
With the scale turned on and placed on a stable surface, press the CAL button and "200.00" will flash in the display, immediately place a total of 200g weight on the scale. The scale will reset itself and will give you a PASS message. Calibration is complete.

OPERATING ENVIRONMENT
The optimum operating temperature for the scale is 50-86° F/10-30°C. Rough handling of the scale will damage the

internal sensor; so you must avoid actions such as shaking or dropping the scale. This is a sensitive piece of electronic equipment and will be affected by things such as moisture, extreme temperature changes, magnetic fields, careless handling and misuse.

AUTOMATIC SHUT-OFF
The scale will automatically shut-off after 60 seconds of inactivity this is to help conserve the battery power. We recommend good quality AAA batteries.

Bedienungsanleitung

Danke für den Kauf dieser Digitalwaage. Bei sachgemäßer Handhabung wird Ihnen diese Waage lange Zeit gute Dienste leisten. Bitte lesen Sie die Bedienungsanleitung sorgfältig.
Display Anzeigen:
Lo = Batterien leer, bitte ersetzen

- **OUEr** = Überlastung! Sofort das aufgelegte Gut entfernen
- **UnSt** = die Unterlage ist nicht stabil oder eben, bitte Waage auf eine ebene, stabile Unterlage stellen
- **rCal** = Waage kann sich nicht wieder auf „0" setzen, bitte neu kalibrieren
- **CAL** = diese Anzeige erscheint wenn Sie den durch das drücken und festhalten der „CAL" Taste den Kalibrierungsprozess einleiten. Bitte lassen Sie die Taste los und folgen zum Abschluss der Kalibrierung den Anweisungen, die auf dem Display erscheinen.
- **PASS** = die Kalibrierung ist erfolgreich abgeschlossen
- **FAIL** = die Kalibrierung ist fehlgeschlagen. Bitte stellen Sie sicher, das die Waage stabil und eben steht und Sie das

richtige Kalibrier Gewicht verwendet haben. Wiederholen sie den Vorgang.

Bedienung

Ein/Aus

Stellen Sie die Waage auf eine ebene, stabile Unterlage mit genügend Abstand zu anderen elektronischen Geräten. Durch das drücken der „ON/OFF" Taste wird die Waage eingeschaltet und es erscheint „0.00" und das Zeichen "⏚" . Jetzt das zu wiegende Gut auf die Auflage legen. Erscheint "⏚", ist der Wiegevorgang abgeschlossen.

Tara Funktion

Stellen Sie die Waage ein, platzieren Sie das Gefäß oder die Wiegehilfe auf der Auflage. Drücken Sie die „Tara" Taste. Auf dem Display erscheint wieder „0.00". Jetzt kann gewogen werden, nach Abschluss des Wiegens wieder die Taste „ZERO" drücken um die Tarafunktion zu beenden.

0-Stellung

Sollte sich die Waage nach Beendigung des Wiegens nicht wieder von selbst auf „0" setzen, bitte pressen Sie kurz die „ZERO" Taste.

Anzeige in verschiedenen Gewicht Einheiten

Durch drücken der „Mode" Taste lässt sich das Gewicht auch in 4 verschiedenen Einheiten anzeigen: g, oz, gn, ct

Kalibrierung

Stellen Sie die Waage auf eine ebene, stabile Unterlage. Durch das drücken der „CAL" Taste erscheint auf dem Display blinkend „ 200.00". Platzieren Sie jetzt ein 200gr. Gewicht auf der Auflagefläche. Die Waage setzt sich jetzt selbst zurück, auf dem Display erscheint „PASS" und die Kalibrierung ist abgeschlossen.

Benutzungsvoraussetzungen

Diese Waage ist zum Einsatz bei Temperaturen von 10-30 Grad Celcius bestimmt. Unsachgemäße Handhabung, wie schütteln und schmeißen, zerstören die empfindlichen Sensoren. Hohe Temperaturen, Feuchtigkeit und starke Temperaturschwankungen sind zu vermeiden. Magnetfelder beeinträchtigen das Wiegeverhalten.

Auto Aus

Nach 60 Sekunden ohne Aktivität schaltet sich die Waage von selbst aus. Bitte verwenden Sie, zum Betrieb nur hochwertige Batterien.